

# The Sensedge Go works seamlessly with RAK BACnet Series.



Model: RAK7437C

BACnet Gateway for LoRaWAN®

## Product Variants Overview

Kaiterra Product Name	Kaiterra SKU
NA RW37 (PoE) BACnet Gateway	GW-37-NA-915M-EG95-NA-POE
EMEA RW37 (PoE) BACnet Gateway	GW-37-EMEA-868M-EG95-E-POE
IN RW37 (PoE) BACnet Gateway	GW-37-IN-868M-EC25-E-POE
AU RW37 (PoE) BACnet Gateway	GW-37-AU-915M-EC25-AU-POE
APAC RW37 (PoE) BACnet Gateway	GW-37-APAC-915M-EC25-E-POE
JP RW37 (PoE) BACnet Gateway	GW-37-JP-915M-EC25-J-POE

## Features

### Hardware

- IP30 industrial-grade enclosure
- PoE (802.3at)
- 1x 10/100/1000M ETH WAN Port
- 4x 10/100/1000M ETH LAN Ports
- 1x 10/100/1000M SFP Port
- 2x Type-A USB3.0 Ports
- 1x USB2.0 Debug port (Type-C connector)
- 2x RS485 Ports
- Single LoRa Concentrator for 8 channels (optional 16 channels with two LoRa Concentrators)
- Backhaul: Ethernet, SFP, 2.4 GHz Wi-Fi, LTE
- Optional connectivity: Satellite communication, Wi-Fi HaLow, 5G Wi-Fi, 5G NR, and 2.4 GHz LoRa
- Supports DC 9-36 V
- External antenna (upgradable)
- Dying gasp
- Reset button
- USB 2.0 to UART Debug port (Type-C Connector)

### Software

#### BACnet Gateway Capabilities

- BACnet/IP Gateway (WisGateOS 2 Extensions): Provides native BACnet/IP integration, enabling bridging of LoRaWAN devices with building management systems (BMS).
- BACnet MQTT Integration: Provides MQTT-based data forwarding for BACnet Gateway data flows.
- BACnet/IP Client Whitelisting: Restricts BACnet/IP access to authorized BMS clients through whitelist-based connection control.
- BMS Compatibility: Supports integration with BACnet/IP-compliant BMS platforms, including Carrier BMS.
- Web UI Configuration: Web-based configuration for BACnet device mapping, whitelist, and parameters.

## LoRaWAN Gateway Capabilities

---

- [WisGateOS 2](#): Operating system for configuring and managing RAK gateways.
- Built-in LoRaWAN Network Server with full v1.0.3 specification support.
- Full LoRaWAN stack support with Semtech SX1303.
- LoRa frame filtering (node whitelisting in Packet Forwarder mode).
- MQTT v3.1 Bridge with TLS encryption for secure data delivery.
- LoRa Frame Buffering in Packet Forwarder mode during network server outages (no data loss).
- Listen Before Talk (optional).

Note: Product specifications are subject to change without notice. Feature availability may differ by model.

## Main Specifications

Feature	Specifications
Computing	IPQ5018 dual-core ARM Cortex-A53 @ 1.0 GHz, 1 GB DDR3 RAM
LoRa Feature	<ul style="list-style-type: none"><li>• SX1303 mPCIe card</li><li>• 8 Channels</li><li>• Frequency: EU868/IN865/RU864/US915/AU915/KR920/AS923</li><li>• Listen Before Talk</li><li>• LoRa Radio: Refer to the LoRa Radio Specifications section for detailed information.</li></ul>
Wi-Fi Feature	<ul style="list-style-type: none"><li>• Frequency: 2.4 GHz (802.11b/g/n/ac/ax)</li><li>• 2x2 MIMO</li><li>• Operation channels: 2.4 GHz: 1-13</li><li>• Wi-Fi Radio: Refer to the Wi-Fi Radio Specifications section for detailed information.</li></ul>
Cellular Feature	<ul style="list-style-type: none"><li>• Nano SIM Card: 12 mm x 9 mm x 0.6 mm</li><li>• Supports Quectel EG95-E/EG95-NA/EC25-E/EC25-AU (IoT/M2M optimized LTE Cat 4 Module)</li><li>• LTE Radio: Refer to the LTE Radio Specifications section for detailed information.</li></ul>
Power Supply	<ul style="list-style-type: none"><li>• PoE (IEEE 802.3at): 42~57 VDC</li><li>• DC 9~36 V</li></ul>
ETH	<ul style="list-style-type: none"><li>• 1 × WAN RJ45 port (10/100/1000 Mbps)</li><li>• 4 × LAN RJ45 ports (10/100/1000 Mbps)</li></ul>
SFP	1 × SFP port (1 Gbps)
Antenna	<ul style="list-style-type: none"><li>• LoRa: 1 RP-SMA connector</li><li>• LTE: 2 SMA connectors</li><li>• 2.4G Wi-Fi: 2 SMA connectors</li></ul>
Ingress Protection	IP30
Enclosure Material	Aluminum
Operating Conditions	<ul style="list-style-type: none"><li>• Operating Temperature: - 20 °C to + 55 °C</li><li>• Operating Humidity: 0 - 95 %RH non-condensing</li></ul>
Installation Method	<ul style="list-style-type: none"><li>• Desktop</li><li>• Wall mounting</li><li>• Din rail mounting</li></ul>

# Hardware

The hardware specification outlines the interfacing of the RAK7437C and its associated functionalities.

## RF Specifications

### LoRa Radio Specifications

Parameter	Specifications
Frequency	EU868/IN865/RU864/US915/AU915/KR920/AS923
Transmit Power	27 dBm (Max)
Receiver Sensitivity	-139 dBm (Min)

### WiFi Radio Specifications

Feature	Specifications
Wireless Standard	IEEE 802.11b/g/n/ac/ax
Operating Frequency	ISM band: 2.412~2.472 GHz
Operation Channels	2.4 GHz: 1-13
Transmit power: per chain (The max power may be different depending on local regulations)	<ul style="list-style-type: none"><li>• 802.11b</li><li>• 1 Mbps: 19 dBm</li><li>• 11 Mbps: 19 dBm</li><li>• 802.11g</li><li>• 6 Mbps: 18 dBm</li><li>• 54 Mbps: 16 dBm</li><li>• 802.11n (2.4 GHz)</li><li>• MCS0 (HT20): 18 dBm</li><li>• MCS7 (HT20): 16 dBm</li><li>• MCS0 (HT40): 17 dBm</li><li>• MCS7 (HT40): 15 dBm</li></ul>
Receiver Sensitivity (Typical)	<ul style="list-style-type: none"><li>• 802.11b</li><li>• 1 Mbps: 95 dBm</li><li>• 11 Mbps: 88 dBm</li><li>• 802.11g</li><li>• 6 Mbps: 90 dBm</li><li>• 54 Mbps: 75 dBm</li><li>• 802.11n (2.4 GHz)</li><li>• MCS0 (HT20): 89 dBm</li><li>• MCS7 (HT20): 72 dBm</li><li>• MCS0 (HT40): 86 dBm</li><li>• MCS7 (HT40): 68 dBm</li></ul>

## LTE Radio Specifications

Feature	Specifications
EG95-E for EMEA Region (Europe, Middle East, and Africa)	<ul style="list-style-type: none"><li>• LTE FDD: B1/B3/B7/B8/B20/B28A</li><li>• WCDMA: B1/B8</li><li>• GSM/EDGE: B3/B8</li></ul>
EG95-NA for North America Region	<ul style="list-style-type: none"><li>• LTE FDD: B2/B4/B5/B12/B13</li><li>• WCDMA: B2/B4/B5</li><li>• LTE-FDD: B1/B3/B5/B7/B8/B20</li></ul>
EC25-E for South Korea, Thailand, India	<ul style="list-style-type: none"><li>• LTE-TDD: B38/B40/B41</li><li>• WCDMA: B1/B5/B8</li><li>• GSM/EDGE: B2/B3/B5/B8</li><li>• LTE-FDD: B1/B2/B3/B4/B5/B7/B8/B28</li></ul>
EC25-AU for Latin America, Australia, and New Zealand Region	<ul style="list-style-type: none"><li>• LTE-TDD: B40</li><li>• WCDMA: B1/B2/B5/B8</li><li>• GSM: B3/B8</li></ul>

Note: Product specifications are subject to change without notice.

## Software

LoRa	Network	Management
BACnet Gateway (LoRaWAN to BACnet/IP)	Wi-Fi AP Mode	Web UI
Gateway OTA Management	Wi-Fi Client Mode	SSH2
LoRaWAN Packet Forwarding (Packet Forwarder, Basics Station)	LTE APN Setup	Firmware Update
Frequency Band Setup	VLAN (802.1Q) Support	Built-in Network Server
Country Code Setup	Uplink Backup	MQTT Bridge
TX Power Setup	Firewall	Ping Watchdog
Data Logger	DHCP Server/Client	
Location Setup		
LoRa Statistics		
Supports Class A and C		
Server Address and Port Setup		

## Certification

- CE Certification
- FCC Certification
- ISED Certification

Additional information available: <https://docs.rakwireless.com/>